

Modbus registers E6600-RS485

REG	DESCRIPTION	READ	WRITE EFFECT IN USUAL WORK	Supported values	New device	Remarks
1	Hardware version	+	-	-	-	
2	Software version	+	-	-	-	
3	Serial number	+	-	-	-	
4	Modbus address	+	+	1-247	1	
5	Modbus baudrate	+	+	1200, 2400, 4800, 9600, 19200, 38400, 57600	9600	
6	Response delay	+	+	1-255	10	
7	Modbus format	+	+	1-4	1	1 = Parity none, Stop bits 1 2 = Parity none, Stop bits 2 3 = Parity odd, Stop bits 1 4 = Parity even, Stop bits 1
9	Alarm status	+	-	-	-	1 - In alarm 0 - Not in alarm
11	Battery power	+	-	-	-	1 - Powered by battery 0 - Not powered by battery
17	Restart	+	+	42330	-	