



PSW 600W-12 : Ref. 027275 - Ref. 027343 
 PSW 1000W-12 : Ref. 027282 - Ref. 027350 
 PSW 1500W-12 : Ref. 027299 - Ref. 027367 

12V > 230V

Inverters - Pure Sine Wave. Dual Sockets + USB. The range of PSW inverters converts your car battery into a 230V power supply for any electrical appliance up to 1500W. The USB socket (5V) will allow you to plug in electrical appliances such as MP3 players, digital cameras...

The Pure Sine Wave output (as opposed to Modified Sine Wave) is a very high quality power supply suitable for high quality and sensitive electrical appliances.

Pure Sine Wave



12 V

- ✓ The power produced is either **identical or slightly better than the power from the public network.**
- ✓ Current peaks are smoothed by the Inverter which **automatically regulates** the power output.
- ✓ **Ideal for sensitive and demanding high quality equipment.**

Simple and effective

✓ **Compact** and delivered with a fix points for, these items are designed to be easily carried or set up permanently in the vehicle.

✓ **2 connection types** for all types of electrical appliances:

- 1 or 2 sockets (230V)
- 1 USB connector (5V)

Safe

- ✓ Thermal protection, ventilated.
- ✓ Protection against overload and short-circuit.
- ✓ Protection against undervoltage and overvoltage.

PSW 600W-12



PSW 1000W-12




PSW 1500W-12



Livré avec :



PSW 600W-12							600 W					
PSW 1000W-12							1000 W					
PSW 1500W-12							1500 W					
ex. 12V • 100Ah	48h	16h	10h	8h	5h30	4h	2h45	2h45	1h20	0h30	0h20	

	Power (W)	Peak Power (W)	Pure Sin Wave	Optimum Efficiency	Input DC	Output AC	Output USB DC	Universal		cm	kg
PSW 600W-12	600	1200	✓	85%	12V	230V	5V - 500mA	✓	✓	23x31x15	2.2
PSW 1000W-12	1000	2000	✓	85%	12V	230V	5V - 500mA	✓	✓	23x39x15	3.4
PSW 1500W-12	1500	3000	✓	85%	12V	230V	5V - 500mA	✓	✓	23x39x15	3.6